

راهنمای کاربر: نصب کانکشن VPN در مک (Mac) PPTP/L2TP





مرحله اول: ابتدا از System Preferences، آیتم Network را انتخاب کنید.

| Image: Show All Personal Appearance Deck Epposé & Language & Security Spolight Hardware Image: Spolight Image: Spolight Image: Spolight Hardware Image: Spolight Image: Spolight Image: Spolight Internet & Wireless Image: Spolight Image: Spolight Image: Spolight MublicMi Image: Spolight Image: Spolight Image: Spolight System Image: Spolight Image: Spolight Image: Spolight Accounts Date & Time Image: Spolight Image: Spolight Image: Spolight Accounts Date & Time Parental Software Spech Startup Disk Time Machine Image: Im | 0 0 | System Prefer | ences | | |
|--|-------------------------|-------------------|-------------------------|---------------------|--------------------|
| Personal Appearance Desktop & Screen Saver Dock Exposé & Sposé & Saver Language & Text Security Spotlight Hardware Image: Security Displays Energy Baser Image: Security Spotlight Spotlight Mathware Image: Security Image: Security Image: Security Image: Security Spotlight MobileMe Image: Society Image: Society <thimage: society<="" th=""> Image: Society</thimage:> | Show All | | | ٩ | |
| Appearance Desk op & Screen Saver Dock Exposé & Spaces Desk op & Text Desk op & Security Desk op & Spotlight Hardware Image: CDS & DVDS Displays Energy Saver Image: CDS & Network Image: CDS & Security Image: CDS & Sound Internet & Wireless MobileMe Image: CDS & Security Image: CDS & Security Image: CDS & Security Image: CDS & Sound | Personal | | | | |
| Appearance Deskop & Dock Exposé & Language & Security Spotlight Hardware Image: Spaces Security Spotlight Dos & DVDs Displays Energy Image: Spaces Mouse Print & Fax Sound Internet & Wireless Image: Spaces Image: Spaces Image: Spaces Image: Spaces Sound System Image: Spaces Image: Spaces< | New | | (3) | Q | |
| Justes IKK Hardware | Appearance Desktop & D | Dock Exposé & Lan | guage & Security | Spotlight | |
| Internet & Wireless Internet & Wireless Internet & Wireless MobileMe Internet & Wireless Internet & Ureless Internet | Hardware | spaces | Text | | |
| CDs & DVDs Displays Energy Saver ink Keyboard Mouse Print & Fax Sound Internet & Wireless Mobile W Image: Source of the sour | | 8 🗾 | | - | |
| Internet & Wireless MobileMe Image: System < | CDs & DVDs Displays Et | nerav Ink Ke | wboard Mouse | Print & Fax | Sound |
| Internet & Wireless MobileMe Image: Sharing System Image: Sharing Accounts Date & Time Image: Sharing Date & Time Image: Sharing Image: Sharing Image: Sharing Matching Image: Sharing Image: Sharing Image: Sharing Image: Sharing Accounts Date & Time Image: Sharing Image: Sharing Image: Sharing Image: Sharing Accounts Date & Time Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Accounts Date & Time Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Accounts Date & Time Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Accounts Date & Time Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Image: Sharing Imag | S | Saver | , | | |
| System Accounts Date & Time Accounts Date & Time Parental Controls Software Speech Startup Disk Time Machine Universal Accounts Date & Time Parental Controls Software Speech Startup Disk Time Machine Universal Accounts Date & Time Parental Controls Software Speech Startup Disk Time Machine Universal Accounts Accounts Controls Status Connected Ethernet is currently active and has the IP address 192.168.40.129. Built-1 Port (2) Not Not Not Configure IPv4: Using DHCP P Not Configure IPv4: Using DHCP P Not Configure IPv4: Using DHCP P Address: 192.168.40.129. Built-1 Port (2) Not Configure IPv4: Using DHCP P Address: 192.168.40.2 Dis Server: 192.168.40.2 Dis Server: 192.168.40.2 Dis Server: 192.168.40.2< | Internet & Wireless | | | | |
| MobileMe Network Sharing System Software Speech Startup Disk Time Machine Operational Access Accounts Date & Time Parental Software Speech Startup Disk Time Machine Operational Access Accounts Date & Time Parental Software Speech Startup Disk Time Machine Operational Access Accounts Date & Time Parental Software Speech Startup Disk Time Machine Operational Access Access Date & Time Access Date & Time Access Date & Time Access Vetwork Network Construct Quercest Date & Time Access Date & Time Access Show All Cocation: Automatic Quercest Status: Connected Ethernet is currently active and has the IP address 192.168.40.129. Built-1 Port (2) Subnet Mask: 255.255.255.0 Router: 192.168.40.2 Dis Search Domains: Iocaldomain Wate Configured Dis Search Domains: Iocaldomain Iocaldomain Iocaldomain Iocaldomain | · 🔼 🛛 🛞 🛛 🕯 | <u>*</u> | | | |
| System Accounts Date & Time Parental Controls Software Update Speech Startup Disk Time Machine Operation of the parental Access Accounts Date & Time Parental Controls Software Update Speech Startup Disk Time Machine Operation of the parental Access Accounts Date & Time Parental Controls Software Update Speech Startup Disk Time Machine Operation of the parental Access Accounts Network Network Network Network Operation of the parental Access Show All Contacted Ethernet is currently active and has the IP address 192.168.40.129. Status: Configure IPv4: Using DHCP Operation of the parental Access Built-i Port (2) Operation IP Address: 192.168.40.129. Status: Status: 255.255.255.0 Router: 192.168.40.2 DNS Server: 192.168.40.2 DNS Search Domains: Docaldomain | MobileMe Network Sh | haring | | | |
| Image: Accounts Image: Accounts Image: Software update Image: Softwar | System | | | | |
| Accounts Date & Time Parental Controls Software Update Speech Startup Disk Time Machine Universal Access | | in (10) | 8 2 | | |
| در صفحه Network، روی علامت + کلیک کنید. Network Show All Location: Automatic Ethernet Connected Built-i Port (1) Not Configured Built-i Port (2) Configure IPv4: Using DHCP IP Address: 192.168.40.129 Subnet Mask: 255.255.0 Router: 192.168.40.2 DNS Server: 192.168.40.2 DNS Server: 192.168.40.2 Search Domains: localdomain | Accounts Date & Time Pa | rental Software S | peech Startup Disk | Time Machine | Universal |
| در صفحه Network، روی علامت + کلیک کنید. Network Show All Cocation: Automatic Connected Built-i Port (1) Status: Connected Ethernet is currently active and has the IP address 192.168.40.129. Subnet Mask: 255.255.255.0 Route: 192.168.40.2 DNS Serve: 192.168.40.2 Search Domains: localdomain | Co | ontrois Update | | | Access |
| در صفحه Network، روی علامت + کلیک کنید. Network Show All Location: Automatic Connected Built-iPort (1) Not Configured Built-iPort (2) Not Configured Status: Connected Ethernet is currently active and has the IP address 192.168.40.129. Configure IPv4: Using DHCP IP Address: 192.168.40.129 Subnet Mask: 255.255.255.0 Router: 192.168.40.2 DNS Server: 192.168.40.2 Search Domains: localdomain | | | | | |
| Show All Show All Location: Automatic Cation: Automatic Status: Connected Ehernet is currently active and has the IP address 192.168.40.129. Distribution Not Configured P Address: 192.168.40.129 P Address: 192.168.40.129 P Address: 192.168.40.129 Status: Configure IPV4: Using DHCP P Address: 192.168.40.129 Dis Server: 192.168.40.2 Dis Server: 192.168.40.2 Search Domains: | | غنيد. | ں علامت + کلیک ک | Netwo، روء | در صفحه r k |
| Show All Contention: Automatic Connected Built-iPort (1) Status: Configure IPv4: Using DHCP Not Configured Configure IPv4: Using DHCP IP Address: IP2.168.40.129 Subnet Mask: 255.255.0 Router: 192.168.40.2 DNS Server: 192.168.40.2 Search Domains: Iocaldomain | 000 | Network | | | |
| Location: Automatic Ethernet Status: Connected Ethernet is currently active and has the IP address 192.168.40.129. Built-i Port (2) IP Address: 192.168.40.129. Subnet Mask: 255.255.255.0 Router: 192.168.40.2 DNS Server: 192.168.40.2 Search Domains: | Show All | | | Q | |
| Location: Automatic <p< td=""><td></td><td></td><td></td><td>_</td><td></td></p<> | | | | _ | |
| Chernet Connected Built-i Port (1) Configured Built-i Port (2) Configured Configure IPv4: Using DHCP IP Address: 192.168.40.129 Subnet Mask: 255.255.255.0 Router: 192.168.40.2 DNS Server: 192.168.40.2 Search Domains: localdomain | Loc | ation: Automatic | | • | |
| Connected Status: Connected Built-i Port (1) S Ethernet is currently active and has the IP address 192.168.40.129. Built-i Port (2) S Configure IPv4: Using DHCP IP Address: 192.168.40.129 Subnet Mask: 255.255.255.0 Router: 192.168.40.2 DNS Server: 192.168.40.2 Search Domains: Iocaldomain | e Ethernet | | Commented | | |
| Built-I Port (1) Address 192.168.40.129. Built-I Port (2) Not Configured IP Address: 192.168.40.129 Subnet Mask: 255.255.255.0 Router: 192.168.40.2 DNS Server: 192.168.40.2 Search Domains: localdomain | Connected | Status: | Ethernet is currently a | ctive and has the I | Р |
| Built-i Port (2) Configure IPv4: Using DHCP IP Address: 192.168.40.129 Subnet Mask: 255.255.255.0 Router: 192.168.40.2 DNS Server: 192.168.40.2 Search Domains: localdomain | Not Configured | | address 192.168.40.1 | 29. | |
| IP Address: 192.168.40.129 Subnet Mask: 255.255.255.0 Router: 192.168.40.2 DNS Server: 192.168.40.2 Search Domains: Iocaldomain | Built-i Port (2) | Configure IPv4: | Using DHCP | | • |
| Subnet Mask: 255.255.255.0 Router: 192.168.40.2 DNS Server: 192.168.40.2 Search Domains: localdomain | not configured | IP Address: | 192.168.40.129 | | |
| Router: 192.168.40.2 DNS Server: 192.168.40.2 Search Domains: localdomain | | Subnet Mask: | 255.255.255.0 | | |
| DNS Server: 192.168.40.2 Search Domains: localdomain | | Router: | 192.168.40.2 | | |
| Search Domains: localdomain | | DNS Server: | 192.168.40.2 | | |
| | | Search Domains: | localdomain | | |
| | | | | | |
| | | | | | |
| | | | | | |
| (Advanced) (?) | | | | Advanced | |
| | | | | Auvanceu | |
| Click the lock to prevent further changes. | + - * | | | Auvanceu | |



مرحله سوم (ساخت کانکشن PPTP): در پنجره ظاهر شده، از لیست Interface گزینه VPN را انتخاب کنید. از لیست VPN Type، گزینه PPTP و در کادر Service Name، عبارت "(ITED VPN (PPTP" را برای ساختن کانکشن وی پی ان PPTP برگزینید و دکمه Create را کلیک کنید.

| e Ethernet Connected | Interface: VPN Type: | VPN PPTP | the for the new service. | os the IP |
|--------------------------------|-------------------------|----------------|--------------------------|----------------|
| Built-i Port Not Configured | Service Name: | ITED VPN (PPT) | P) | as the ir |
| Built-i Port | | | Cancel Create | • |
| Ļ | | IP Address: | 192.168.40.135 | |
| | | Subnet Mask: | 255.255.255.0 | |
| | | Router: | 192.168.40.2 | |
| | | DNS Server: | 192.168.40.2 | |
| | Se | arch Domains: | localdomain | |
| | | | G | Advanced) (?) |

ساخت کانکشن L2TP: برای ساختن کانکشن L2TP، از لیست VPN Type، گزینه L2TP over IPSec را انتخاب کرده وعبارت "ITED VPN L2TP" را در کادر Service Name وارد کنید و دکمه Create را کلیک کنید. (فقط عبارت داخل گیومه را وارد کنید.)

| 0 0 0 | Network | |
|--|---|-----|
| Show All | ٩ | |
| Ethernet Connected Built-i Port Not Configured Built-i Port Not Configured ITED VPN (PPTP) Not Connected | Select the interface and enter a name for the new service. Interface: VPN VPN Type: L2TP over IPSec Service Name: ITED VPN (L2TP) Configuration Cancel Create Telephone Number: Account Name: Password: Connect | |
| + - *- | Show modem status in menu bar Advanced | ? |
| Click the lock to | o prevent further changes. Assist me Revert App | oly |



مرحله چهارم: در صفحه ظاهر شده، برای تنظیمات سرور اطلاعات مربوط به وی پی ان سرور خود را وارد کنید.

در کادر Server Address، آدرس وی پی ان سرور و در کادر Account Name، نام کاربری خود را وارد کنید.

| | Network | | |
|--|---|---|--|
| | Location: Automatic | ÷ | |
| e Ethernet Connected | Status: | Not Configured | |
| ● Built-1 P Not Configu ● Built-i P Not Configu | ort (1) red Configuration: | Default | |
| ITED VPN Not Configu | PPTP) Server Address: red Account Name: Encryption: | ادرس سرور را وارد کنید نام کاریری خود را وارد کنید (Automatic (128 bit or 40 bit) | |
| | | Authentication Settings) Connect | |
| | | | |
| + - 0- | Show VPN status | in menu bar Advanced) (?) | |
| 📶 Click the | ock to prevent further changes. | Assist me Revert Apply | |
| ردن پسورد (رمز عبور) خود د. | Authenticatio جهت وارد ک پ کنید و دکمه OK را کلیک کنی | من PPTP: برروی دکمه n Settings Password، کلمه عبور داده شده را تای | مرحله پنجم - کانک کلیک کنید. در کادر |
| | | | |



| $\bigcirc \bigcirc \bigcirc$ | Network | |
|---|---|--|
| Show All | Q | |
| Ethernet Connected Built-i Port (1) Not Configured Built-i Port (2) Not Configured ITED VPN (PPTP) Not Configured | User Authentication: Password: RSA SecurID Certificate Select Kerberos CryptoCard Cancel OK Account Name: Encryption: Automatic (128 bit or 40 bit) Authentication Settings Connect | |
| + - *- | Show VPN status in menu bar Advanced ? | |
| Click the lock to | prevent further changes. Assist me Revert Apply | |
| | | |

مرحله پنجم - کانکشن L2TP: در کادر Password، کلمه عبورداده شده و سپس Shared Secret را نیز وارد کنید و روی دکمه OK کلیک کنید. مشترکین آیتد جهت دریافت اطلاعات مربوطه می توانند با پشتیبانی تماس بگیرند.

| 0 🔴 0 | Network | |
|--|---|--------------|
| Show All | | ٩ |
| Ethernet Connected Built-i Port (1) Not Configured Built-i Port (2) Not Configured ITED VPN (PPTP) ITED VPN (PPTP) | User Authentication: Password: RSA SecurID Certificate Select Kerberos CryptoCard Machine Authentication: | |
| ITED VPN (L2TP) Not Configured | Certificate | ect) |
| | Group Name: (Optional) | |
| | Cancel | К |
| + - \$- | ✓ Show VPN status in menu bar | Advanced ? |
| Click the lock to | prevent further changes. Assist me | Revert Apply |





مرحله ششم: جهت دسترسی آسانتر به کانکشن ساخته شده می توانید کادر Show VPN status in menu bar را کلیک کنید تا تیک دار شود. سپس دکمه ...Advanced را کلیک کنید.

| 0 0 | Network | |
|-------------------------------------|---|-------------------------|
| Show All | ٩ | |
| l | ocation: Automatic | |
| | | |
| Sonnected | Status: Not Connected | |
| ⊖ Built-i Port (1) @ ** | | |
| - Built-i Port (2) Q | | |
| • Not Configured | Configuration: Default | |
| ITED VPN (PPTP) Not Connected | Server Address: server address | |
| | Account Name: username | |
| | Encryption: Automatic (128 bit or 40 bit) | |
| | Connect | |
| | Connect | |
| | | |
| | | |
| | Show VPN status in menu bar | |
| + - 0- | | |
| Click the lock to prever | nt further changes. Assist me Revert Apply | |
| | | |
| Send را تیک بزنید و دکمه OK را کلیک | برگه Options، گزینه all traffic over VPN connection ا | مرحله هفتم: در ب |
| | | کنید. |
| 000 | Network | - |
| Show All | Q | |
| | | |
| ITED VPN (PPTP) | ation: Automatic 0. | |
| Option | S VPN on Demand TCP/IP DNS Proxies | |
| | Status: Not Connected | |
| Built-1, Port (1) Built- | Session Disconnect when switching user accounts | |
| - nelli-i Portizi o P | Disconnect when user logs out | |
| " Der Constantes" - Spec | Send all traffic over VPN connection | |
| | Disconnect if idle for 10 minutes | |
| | Advanced | |
| | Use verbose logging | |
| | | |
| | | |
| | | |
| | | |
| | | |
| | | |
| te | | |
| (?) | CancelOK | |
| A CHICK THE TOCK IS DREVENT | | |



مرحله هشتم: کانکشن شما در این مرحله ساخته شده و می توانید جهت برقراری ارتباط با سرور روی دکمه Connect کلیک کنید. ارتباط با سرور پس از تایید از هویت کاربری شما برقرار می گردد.

مرحله نهم: شما می توانید در دفعات آتی، با کلیک بر روی آیکن کانکشن کلیک کنید و برای وصل شدن به سرور، گزینه "Connect to ITED VPN (PPTP) ویا "Connect to ITED VPN (L2TP)" را که قبلا ساختید، کلیک کرده تا ارتباط برقرار گردد. در صورت بروز هر گونه مشکل و یا سوالی میتوانید با تیم فنی ما مکاتبه نمایید.





موفق و پیروز باشید. تهیه و تدوین از: ITED بروزرسانی: یکشنبه ۱۴ خرداد ۱۳۹۱

تماس با ما: وب سلیت : https://ssl-url.net/allvpn.eu و المحلي ا